

# Dimmer Compatibility Report

## LED Linear Luminaires



Leviton		Lutron		Phillips	STANDARD
ILLUMATECH IP710-LFZ	DNADVSTV	Maestro MS-Z101	Nova T NTSTV	Sunrise SR1200ZTUNV	61989 Transceiver

### LED Wrap

		Leviton	DNADVSTV	Lutron	Maestro MS-Z101	Nova T NTSTV	Phillips	STANDARD
66174	LSW/4FT/34W/40K/120-277/A1/STD	✓	✓	✓	✓	✓	✓	✓
66261	LWR4/120-277/42W/40K/FR/A2/STD	✓	✓	✓	✓	✓	✓	✓



Leviton		Lutron		Phillips
ILLUMATECH IP710-LFZ	DNADVSTV	Maestro MS-Z101	Nova T NTSTV	Sunrise SR1200Z-TUNV

### LED Vapor Tight

		Leviton	DNADVSTV	Lutron	Maestro MS-Z101	Nova T NTSTV	Phillips
66196	LSV/N/35W/40K/120-277/DD1/FP/A1/STD	✓	✓	✓	✓	✓	✓
66197	LSV/N/40W/40K/120-277/DD1/FP/A1/STD	✓	✓	✓	✓	✓	✓
66198	LSV/N/35W/40K/347/DD1/FP/A1/STD	✓	✓	✓	✓	✓	✓
66199	LSV/N/52W/40K/347/DD1/FP/A1/STD	✓	✓	✓	✓	✓	✓



Leviton		Lutron		STANDARD
IP710-DL	NFTV	NFTV		61989 Transceiver

### LED Striplight

		Leviton	NFTV	Lutron	NFTV	STANDARD
65034	LSS/2FT/20W/40K/120-277/STD	✓	✓	✓	✓	✓
65035	LSS/4FT/41W/40K/120-277/STD	✓	✓	✓	✓	✓
65036	LSS/8FT/78W/40K/120-277/STD	✓	✓	✓	✓	✓
66082	LSS/4FT/32W/40K/120-277/A1/STD	✓	✓	✓	✓	✓
66127	LSS/8FT/65W/40K/120-277/A1/STD	✓	✓	✓	✓	✓
66170	LSS/S2/4FT/40W/40K/120-277/A1/STD	✓	✓	✓	✓	✓
66171	LSS/S2/8FT/75W/40K/120-277/A1/STD	✓	✓	✓	✓	✓
66172	LSS/4FT/40W/40K/347/A1/STD		✓	✓	✓	✓
66173	LSS/8FT/75W/40K/347/A1/STD		✓	✓	✓	✓

\*NOTE: The above table shows dimmers that have been tested and have demonstrated proper operation under normal conditions. Each installation being unique, various factors such as load, common neutrals or other electrical products on the circuit can, in certain instances, cause variance in system performance. Read and comply to the dimmer installation instructions. Consult dimming system manufacturer for additional support in operation. Standard recommends to use dimmers designed to work with LED lamps. Older dimmers designed for incandescent lamps may cause erratic operation. Do not mix lamps of different wattages or types on the same dimming circuit. Some dimmers may require more than one lamp for stable operation. The maximum number of lamps is determined by the dimmer wattage rating with LEDs. Be careful, these dimmers have different ratings depending on the lamp type. Again, refer to the dimmer installation instructions. For example, if the dimmer rating is 150W with LED, a user may use up to fifteen (15) 10W PAR30.